

MIXERS

TRIPLE-BALANCED

LO = +10 dBm

IMPROVED DYNAMIC RANGE

SURFACE MOUNT



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
1 - 2500	1 - 2000	6.5/8.5	8.0/9.5	45/35	35/25	28/20	40/30	26/20	22/16	133	2	SMD-C8
5 - 1000	5 - 1000	6.5/8	7.5/9.5	35/20	40/30	30/23	30/20	30/20	25/20	159	1	SLD-K5
25 - 1800	25 - 1000	7.5/8.5	8/9	50/30	45/25	35/20	30/15	25/15	23/15	133	2	SMD-C5
50 - 2500	50 - 880	7/8.5	8/9.2	44/35	--/--	40/30	38/28	--/--	25/20	133	2	SMD-C7
800 - 3550♦	800 - 2500	--/--	10/11.8	--/--	--/--	28/20	--/--	--/--	23/15	133	2	SMD-C9**

THROUGH HOLE (RELAY)



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05 - 200	0.05 - 200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	102	3	CLP-206
10 - 1000	5 - 500	6/7.5	7/8	50/40	40/30	30/20	40/25	30/18	25/15	102	4	CLP-2P4
0.05 - 1500	0.05 - 500	6/7.5	7/9	25/20	35/25	30/20	25/20	35/25	25/15	102	3	CLP-2H5
0.05 - 2000	0.05 - 500	6/8	7/9	25/20	40/30	30/20	25/20	40/30	25/15	102	3	CLP-2B6
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	35/20	27/20	103	3	CLP-205
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	103	3	CLP-210
10 - 2000	10 - 1000	6/8	6.5/8	32/25	35/25	35/25	33/20	30/20	30/20	105	5	CLP-3E6
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	105	6	CLP-305
10 - 3000	10 - 800	6.3/8	6.5/8.5	35/25	35/25	35/25	30/20	30/20	30/20	105	5	CLP-3B8
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	105	6	CLP-310

NOTES:

- 1dB Compression Point = +5 dBm (Typ)
 - IP3 (Input) = +18 dBm (Typ)
 - As IF frequency decrease below LF towards DC, conversion loss increases up to 8 dB higher than maximum.
 - Maximum Input Power without damage = 250 mW ave. cw
- ♦ LO Frequency is specified from 600 to 2595 MHz
 ** UB identifies the full bandwidth specification

ALL MODELS	MODEL SMD-C7
XMB= 2LF to HF/2	XMB = 750 - 1000 MHz
FULL BAND = LF to HF	LB = 750 - 1200 MHz
LB= LF to 10LF	UB =1200 - 2500 MHz
MB = 10LF to HF/2	
UB= HF/2 to HF	

PIN-OUT TABLE

	RF	LO	IF	GND	CASE GND	NO CONN.
#1	4	1	5	2,3,6	--	--
#2	1	2	3	4,5,6	--	--
#3	1	8	3	2,5,6,7	2,5,6,7	4
#4	8	1	3	2,5,6,7	2,5,6,7	4
#5	4	1	2	3	3	--
#6	1	4	2	3	3	--

GND = Ground externally

For pin location and package outline drawings, see back pages.

*Connect pins together externally.


MIXERS

TRIPLE-BALANCED

$LO = +10 \text{ dBm}$

IMPROVED DYNAMIC RANGE

THROUGH HOLE (TO -CAN)



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.5-200	0.5-200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	123	1	CLP-506
10-2500	10-1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	104	1	CLP-505
10-2500	10-1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	122	2	CLP-605
500-3700	500-1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	122	2	CLP-610

FLAT PACK



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	101	3	CLF-105
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	101	3	CLF-110

COAXIAL



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			OUTLINE DRAWING	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05 - 200	0.05 - 200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	110	4	CLK-706*
10 - 2000	10 - 1000	6/8	6.5/8.5	32/25	35/25	35/20	33/20	30/20	25/20	110	4	CLK-7A6S ■
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/20	35/20	30/20	27/20	110	4	CLK-705S
10 - 3000	10 - 800	6.3/8	6.5/8.5	35/25	35/25	35/25	30/20	30/20	30/20	110	4	CLK-7B8S
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	110	4	CLK-710S

NOTES:

- 1dB Compression Point = +5 dBm (Typ)
- IP3 (Input) = +18 dBm (Typ)
- As IF frequency decrease below LF towards DC, conversion loss increases up to 8 dB higher than maximum
- Maximum Input Power without damage = 250 mW ave. cw

* Connector style: "B" = BNC, "T" = TNC, "N" = Type N, "S" = SMA

■ Double Balanced Model (IP3 & 1dB comp. pt. 3 dB lower than specified.)

PIN-OUT TABLE

	RF	LO	IF	GND	CASE GND	NO CONN.
#1	2	5	11	All Others	All Others	--
#2	1	3	2	4	4	--
#3	1	4	5	All Others	All Others	--
#4	1	3	2	--	--	--

GND = Ground externally

For pin location and package outline drawings, see back pages.

XMB= 2LF to HF/2
FULL BAND = LF to HF
LB= LF to 10LF
MB = 10LF to HF/2
UB= HF/2 to HF

MIXERS

TRIPLE-BALANCED

LO = +13 dBm

HIGH DYNAMIC RANGE



THROUGH HOLE (RELAY)

FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.5 - 2000	0.2 - 600	5.8/8	7.2/9.5	60/45	35/30	30/25	55/40	30/25	25/20	105	1	CMP-3A6
10 - 4200	10 - 1000	7.5/8.5	7.5/11	35/25	40/25	35/25	35/20	35/25	27/20	105	2	CMP-3A8



THROUGH HOLE (TO-CAN)

FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
5 - 2500	10 - 1000	6.4/8.5	7/9.5	33/25	35/25	25/20	33/20	30/25	27/20	104	3	CMP-6A7

NOTES:

1. 1dB Compression Point = +10 dBm (Typ)
2. IP3 (Input) = +20 dBm (Typ)
3. As IF frequency decrease below LF towards DC, conversion loss increases up to 8 dB higher than maximum.
4. Maximum Input Power without damage = 500 mW ave. cw

PIN-OUT TABLE

	RF	LO	IF	GND	CASE GND	NO CONN.
#1	1	4	2	3	3	--
#2	4	1	2	3	3	--
#3	2	8	11	All Others	--	--

GND = Ground externally

For pin location and package outline drawings, see back pages.

XMB= 2LF to HF/2
 FULL BAND = LF to HF
 LB= LF to 10LF
 MB = 10LF to HF/2
 UB= HF/2 to HF

MIXERS

TRIPLE-BALANCED

LO = +17 dBm

VERY HIGH DYNAMIC RANGE

SURFACE MOUNT



133



159

FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
5 - 1000	5 - 1000	6.5/8	7.5/9.5	35/20	40/30	30/23	30/20	30/20	25/20	159	1	SLD-K5M
25 - 1800	25 - 1000	7.5/8.5	8/9	50/30	45/25	35/20	35/15	25/15	23/15	133	2	SMD-C5M
750 - 2500	50 - 880	7/8.5	8/9.2	44/35	--/--	40/30	38/28	--/--	25/20	133	2	SMD-C7M*

*XMB = 750 - 1000 MHz

*LB = 750 - 1200 MHz

*UB = 1200 - 2500 MHz



102



103



105

THROUGH HOLE (RELAY)

FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05-200	0.05-200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/20	102	3	CMP-206
5-1200	1-1200	6/7	7/8.5	50/35	45/30	40/25	40/30	35/25	35/20	102	4	CMP-231
10-2500	10-1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	103	3	CMP-205
10-2500	10-1000	7.0/8.0	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	105	5	CMP-305
10-3000	10-1000	8/11	10/12	29/20	25/18	23/14	27/20	25/12	23/16	102	3	CMP-2A8
500-3700	500-1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	103	3	CMP-210
500-3700	500-1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	105	5	CMP-310

NOTES:

- 1dB Compression Point = +14 dBm (Typ)
- IP3 (Input) = +26 dBm (Typ)
- As IF frequency decrease below LF towards DC, conversion loss increases up to 8 dB higher than maximum.
- Maximum Input Power without damage = 500 mW ave. cw

XMB= 2LF to HF/2
FULL BAND = LF to HF
LB= LF to 10LF
MB = 10LF to HF/2
UB= HF/2 to HF

PIN-OUT TABLE

	RF	LO	IF	GND	CASE GND	NO CONN.
#1	4	1	5	2,3,6	--	--
#2	1	2	3	4,5,6	--	--
#3	1	8	3	2,5,6,7	2,5,6,7	4
#4	1	3,4*	8	2,5,6,7	2,5,6,7	--
#5	1	4	2	3	3	--

* Pins must be connected together

GND = Ground externally

For pin location and package outline drawings, see back pages.

MIXERS

TRIPLE-BALANCED

$LO = +17 \text{ dBm}$

VERY HIGH DYNAMIC RANGE

THROUGH HOLE (TO-CAN)



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05 - 200	0.05 - 200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	123	1	CMP-506
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	104	1	CMP-505
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	122	2	CMP-605
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	122	2	CMP-610

FLAT-PACK



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	101	3	CMF-105
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	101	3	CMF-110

COAXIAL



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05 - 200	0.05 - 200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	110	4	CMK-706*
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	110	4	CMK-705S
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	110	4	CMK-710S

NOTES:

- 1dB Compression Point = +14 dBm (Typ)
- IP3 (Input) = +26 dBm (Typ)
- As IF frequency decrease below LF towards DC, conversion loss increases up to 8 dB higher than maximum.
- Maximum Input Power without damage = 500 mW ave. cw

XMB= 2LF to HF/2
FULL BAND = LF to HF
LB= LF to 10LF
MB = 10LF to HF/2
UB= HF/2 to HF

* Connector style: "B" = BNC, "T" = TNC,
N" = Type N, "S" = SMA

PIN-OUT TABLE

	RF	LO	IF	GND	CASE GND
#1	2	5	11	All Others	All Others
#2	1	3	2	4	4
#3	1	4	5	2,3,6,7,8	2,3,6,7,8
#4	1	3	2	--	--

GND = Ground externally

For pin location and package outline drawings, see back pages.

MIXERS

TRIPLE-BALANCED

LO = +23 dBm

SUPER HIGH DYNAMIC RANGE

SURFACE MOUNT



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
5 - 1000	5 - 1000	6.5/8	7.5/9.5	35/20	40/30	30/23	30/20	30/20	25/20	159	1	SLD-K5H
25 - 1800	25 - 1000	7.5/8.5	8/9	50/30	45/25	35/20	35/15	25/15	23/15	133	2	SMD-C5H
750 - 2500	50 - 880	7/8.5	8/9.2	44/35	--/--	40/30	38/28	--/--	25/20	133	2	SMD-C7H*

*XMB = 750 - 1000 MHz

*LB = 750 - 1200 MHz

*UB = 1200 - 2500 MHz



THROUGH HOLE (RELAY)

FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05 - 200	0.05 - 200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	102	3	CHP-206
0.1 - 500	0.5 - 500	5.3/6	5.3/7.5	40/20	46/35	40/30	37/23	46/35	40/30	102	3	CHP-2B3
0.1 - 1000	0.01 - 500	5.3/7.5	7.5/9.5	40/20	40/30	30/25	37/23	40/25	25/20	102	3	CHP-2A4
10 - 2400	5 - 1000	7/8.5	8/10	28/20	26/20	25/20	28/20	26/20	25/20	102	3	CHP-2B7
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	103	3	CHP-205
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	105	4	CHP-305
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	103	3	CHP-210
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	105	4	CHP-310

NOTES:

- 1dB Compression Point = +20 dBm (Typ)
- IP3 (Input) = +30 dBm (Typ)
- As IF frequency decrease below LF towards DC, conversion loss increases up to 8 dB higher than maximum.
- Maximum Input Power without damage = 1 Watt ave. cw

XMB= 2LF to HF/2
FULL BAND = LF to HF
LB= LF to 10LF
MB = 10LF to HF/2
UB= HF/2 to HF

PIN-OUT TABLE

	RF	LO	IF	GND	CASE GND	NO CONN.
#1	4	1	5	2,3,6	--	--
#2	1	2	3	4,5,6	--	--
#3	1	8	3	2,5,6,7	2,5,6,7	4
#4	1	4	2	3	3	--

GND = Ground externally

For pin location and package outline drawings, see back pages.

MIXERS

TRIPLE-BALANCED

LO = +23 dBm

SUPER HIGH DYNAMIC RANGE

THROUGH HOLE (TO-CAN)



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05 - 200	0.05 - 200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	123	1	CHP-506
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	104	1	CHP-505
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	122	2	CHP-605
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	122	2	CHP-610

FLAT-PACK



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	101	3	CHF-105
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	101	3	CHF-110



COAXIAL

FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05 - 200	0.05 - 200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	110	4	CHK-706*
0.1 - 500	0.01 - 500	5.3/6	5.3/7.5	47/20	46/35	40/30	47/40	46/35	40/30	110	4	CHK-7M3*
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	110	4	CHK-705S
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	110	4	CHK-710S

NOTES:

1. 1dB Compression Point = +20 dBm (Typ)
2. IP3 (Input) = +30 dBm (Typ)
3. As IF frequency decrease below LF towards DC, conversion loss increases up to 8 dB higher than maximum.
4. Maximum Input Power without damage = 1 Watt ave. cw

*Connector style: "B" = BNC, "T" = TNC,
"N" = Type N, "S" = SMA

PIN-OUT TABLE

	RF	LO	IF	GND	CASE GND	NO CONN.
#1	2	5	11	All Others	All Others	--
#2	1	3	2	4	4	--
#3	1	4	5	2,3,6,7,8	2,3,6,7,8	--
#4	1	3	2	--	--	--

GND = Ground externally

For pin location and package outline drawings, see back pages.

XMB = 2LF to HF/2
FULL BAND = LF to HF
LB = LF to 10LF
MB = 10LF to HF/2
UB = HF/2 to HF



MIXERS

TRIPLE-BALANCED

LO = +27 dBm

ULTRA HIGH DYNAMIC RANGE

THROUGH HOLE (RELAY)



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05 - 200	0.05 - 200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	102	1	CVP-206
0.5 - 500	0.2 - 500	6/7.5	7.5/8.5	47/40	46/35	35/25	47/40	46/35	35/25	102	1	CVP-2K3
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	103	1	CVP-205
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	103	1	CVP-210
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	105	2	CVP-305
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	105	2	CVP-310

THROUGH HOLE (TO-CAN)



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05 - 200	0.05 - 200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	123	3	CVP-506
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	104	3	CVP-505
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	122	4	CVP-605
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	122	4	CVP-610

NOTES:

- 1dB Compression Point = +24 dBm (Typ)
- IP3 (Input) = +34 dBm (Typ)
- As IF frequency decrease below LF towards DC, conversion loss increases up to 8 dB higher than maximum.
- Maximum Input Power without damage = 1.5 Watts ave. cw

XMB= 2LF to HF/2
FULL BAND = LF to HF
LB= LF to 10LF
MB = 10LF to HF/2
UB= HF/2 to HF

PIN-OUT TABLE

	RF	LO	IF	GND	CASE GND	NO CONN.
#1	1	8	3	2,5,6,7	2,5,6,7	4
#2	1	4	2	3	3	--
#3	2	5	11	all others	all others	--
#4	1	3	2	4	4	--

GND = Ground externally

For pin location and package outline drawings, see back pages.


MIXERS

TRIPLE-BALANCED

LO = +27 dBm

ULTRA HIGH DYNAMIC RANGE

FLAT PACK



FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	101	1	CVF-105
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	101	1	CVF-110



COAXIAL

FREQUENCY RANGE (MHz)		CONVERSION LOSS (dB)		LO-RF ISOLATION (dB)			LO-IF ISOLATION (dB)			PACKAGE	PIN OUT	MODEL
RF/LO	IF	XMB TYP/MAX	FULL BAND TYP/MAX	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN	LB TYP/MIN	MB TYP/MIN	UB TYP/MIN			
0.05 - 200	0.05 - 200	5.5/6.5	6.5/7	45/30	50/45	45/40	35/25	40/35	35/30	110	2	CVK-706*
10 - 2500	10 - 1000	7/8	7.5/8.5	55/35	45/30	35/25	35/20	30/20	27/20	110	2	CVK-705S
500 - 3700	500 - 1000	--/--	9.5/11.5	45/25	45/25	45/25	40/20	40/20	40/20	110	2	CVK-710S

NOTES:

1. 1dB Compression Point = +24 dBm (Typ)
2. IP3 (Input) = +34 dBm (Typ)
3. As IF frequency decrease below LF towards DC, conversion loss increases up to 8 dB higher than maximum.
4. Maximum Input Power without damage = 1.5 Watts ave. cw

* Connector style: "B" = BNC, "T" = TNC,
"N" = Type N, "S" = SMA

XMB= 2LF to HF/2
FULL BAND = LF to HF
LB= LF to 10LF
MB = 10LF to HF/2
UB= HF/2 to HF

PIN-OUT TABLE

	RF	LO	IF	GND	CASE GND
#1	1	4	5	2,3,6,7,8	2,3,6,7,8
#2	1	3	2	--	--

GND = Ground externally

For pin location and package outline drawings, see back pages.